

RDC-DD is built-in our EV Charger.  
Connect to an external Type A RCD when doing the installation.

# EV CHARGER

## EV22KW/DLB/T2-V2

|  |                         |
|--|-------------------------|
| <b>Categorization</b>                              | OCPP1.6 Version         |
| <b>Maximum Power</b>                               | 22kW                    |
| <b>Input voltage</b>                               | AC400V 3Phase           |
| <b>Output voltage / current</b>                    | 230-400V, 6A-32A        |
| <b>Input frequency</b>                             | 50/60Hz                 |
| <b>Cards</b>                                       | 2 on/off cards provided |
| <b>Display</b>                                     | LED lights              |
| <b>RFID</b>  | ✔                       |
| <b>DLB (Solar)</b>                                 | ✔                       |
| <b>WI-FI</b>                                       | ✔                       |
| <b>APP (Remote)</b>                                | ✔                       |
| <b>Bluetooth</b>                                   | ✔                       |
| <b>Over voltage &amp; under voltage protection</b> | ✔                       |
| <b>Emergency stop</b>                              | ✔                       |
| <b>Over current protection</b>                     | ✔                       |
| <b>CP signal short circuit protection</b>          | ✔                       |
| <b>Over temperature protection</b>                 | ✔                       |
| <b>Lightning protection</b>                        | ✔                       |
| <b>Contractor adhesion protection</b>              | ✔                       |
| <b>Protection degree</b>                           | IP65                    |
| <b>Environment temperature</b>                     | -25°C ~ +55°C           |
| <b>Maximum altitude</b>                            | < 2000m                 |
| <b>Charging cable length</b>                       | 8 Metres                |



### Solar Dynamic Loading Box

